



SPD-2P 衛星二分配器



SPD-3P 衛星三分配器



SPD-4P 衛星四分配器



SPD-6P 衛星六分配器



SPD-8P 衛星八分配器

阻抗: 75Ω

型號		SPD-2P	SPD-3P	SPD-4P	SPD-6P	SPD-8P	
頻率範圍		5~2350MHz	5~2350MHz	5~2350MHz	5~2350MHz	5~2350MHz	
幹線損失	5~76MHz	4.0	7.0	8.2	12.0	13.5	
	76~222MHz	4.2	6.8	8.0	10.0	12.0	
	222~770MHz	4.5	7.2	8.5	11.0	13.0	
	770~1489MHz	6.0	8.5	10.0	14.0	15.0	
	1489~2150MHz	7.0	9.0	12.0	16.0	18.0	
	2150~2602MHz	7.5	11.0	14.0	19.0	22.0	
反射損失	IN	5~76MHz	10.0	8.0	8.0	8.0	8.0
		76~222MHz	12.0	12.0	10.0	8.0	10.0
		222~770MHz	12.0	12.0	10.0	10.0	10.0
		770~1489MHz	12.0	12.0	10.0	10.0	12.0
		1489~2150MHz	8.0	12.0	8.0	10.0	10.0
		2150~2602MHz	8.0	8.0	5.0	8.0	8.0
	OUT	5~76MHz	8.0	6.0	8.0	6.0	5.0
		76~222MHz	18.0	18.0	20.0	20.0	20.0
		222~770MHz	15.0	15.0	10.0	12.0	10.0
		770~1489MHz	10.0	8.0	10.0	10.0	8.0
		1489~2150MHz	10.0	6.0	10.0	8.0	8.0
		2150~2602MHz	8.0	5.0	8.0	7.0	6.0
隔離度	5~76MHz	12.0	16.0	20.0	18.0	20.0	
	76~222MHz	20.0	22.0	28.0	25.0	25.0	
	222~770MHz	22.0	22.0	23.0	22.0	22.0	
	770~1489MHz	22.0	22.0	22.0	22.0	20.0	
	1489~2150MHz	20.0	20.0	20.0	20.0	18.0	
	2150~2602MHz	20.0	20.0	18.0	18.0	16.0	
駐波比 V.S.W. R	5~76MHz	2.4	3.1	2.4	3.1	3.6	
	76~222MHz	1.4	1.4	1.3	1.3	1.3	
	222~770MHz	1.6	1.6	2.1	1.8	2.1	
	770~1489MHz	2.1	2.4	2.1	2.1	2.4	
	1489~2150MHz	2.1	3.1	2.1	2.4	2.4	
	2150~2602MHz	2.4	3.6	2.4	2.7	3.1	
尺寸(不含接頭)長*寬*高		5.2*6.0*2.3CM	5.2*6.0*2.3CM	7.5*6.0*2.3CM	12*6.0*2.3CM	12*6.0*2.3CM	